

HALO

INSTALLATION INSTRUCTIONS FOR L-902 HALO-FLEX CONNECTOR

NOTE: For use with L-650 Series Track system ONLY
Electrical Ratings: 120V, 60HZ, 20A

STEP 1. Power must be fed to the track via the L901, L903, L904, L905 or L906

STEP 2. Insert each end of connector into track system. If connector does not slide easily into track, DO NOT FORCE. Track connector is polarized. Turn connector around and use opposite ends. Ground contact is on the same side as polarity groove in track.

STEP 3. After installation into track, tighten screws at each end of connector to secure to track.

698484