## **HALO**


## Installation Instructions for L-942 Halo-2 Flex Joiner USE ONLY WITH HALO L-640 SERIES TRACK SYSTEM ONLY

NOTE: Halo-2 connectors will fit only Halo-2 Power-Trac. All Halo-2 Power-Trac is shipped from the factory with a "Left" dead end installed.

10

CAUTION: This is not a power feed connector. Power must be fed to the track via the L-941, L-943, L-945, L-946 or L-947.

- Step 1. Locate small arrow on the flex connector body and align with polarity groove on the track (See Fig. 1).
- Step 2. Insert into the open end of the track and push fully into place.
- Step 3. Secure by tightening screw near the arrow (See Fig. 2).
- Step 4. Remove plastic end cap from the other track and install the other end of the L-942 in a similar manner making certain that polarity groove on the track sections are in line (See Fig. 3).





Halo Lighting 400 Busse Road 696366