

HALO

Installation Instructions for L-945-R Halo-2 "Right" "T" Connector

USE ONLY WITH HALO L-640 SERIES TRACK SYSTEM ONLY

NOTE: Halo-2 connectors will fit only Halo-2 Power-Trac. All Halo-2 Power-Trac is shipped from the factory with a "Left" dead end installed.

The L-945-R comes with two right polarized ends and one left polarized end. The right end (denoted by the arrow on the right side of the ends) can be installed directly into the open end of the track as shipped from the factory. However, the left end of the L-945-R can be installed only after the left dead end is removed and discarded from the track. If no other connectors will be used, the right end of the track must be terminated with the right dead end provided.

Step 1. Insert the ends of the connector into the respective ends of the Power-Trac. Polarity arrow on connector must be on the same side as polarity groove of track section (See Fig. 1). Secure by tightening screws at the tips of the connector until snug. Do not over tighten since this may distort the track.

NOTE: If used as power feed point follow this procedure.

Step 1. Remove plastic cover.

Step 2. Pull supply wires through the center and attach "hot" wires to unused terminals marked "1" and "2." Attach neutral wire to "NEUT" terminal. Finally, attach ground wire to green ground screw marked "GND" $\frac{1}{8}$ " provided on back plate (See Fig. 2).

Step 3. Reinstall plastic cover.

