

by § signify

LP904P NC Lightscape White R9003
LP904P NC Lightscape Grey R7043 30%




Technical drawing of the 1000 Series Linear Actuator showing front and side views with dimensions.

Front View Dimensions:




- Overall height: 150
- Mounting bracket height: 69
- Mounting bracket width: 40,4

Side View Dimensions:

- Overall length: 1350
- Stroke length: 120



For more detailed mounting instruction, please consult your Signify representative for the NatureConnect system installation manual.



Electrical characteristics	
I max (A)	12.6
T ref (Us)	150
MCB	Max n. of lumin.
B-10 A	16
B-16 A	20
C-10 A	16
C-16 A	20



- The luminaire shall be installed by a qualified electrician and wired in accordance with the latest IEE electrical regulations or the national requirements.
- The light source of this luminaire is not replaceable; when the light source reached its end of life the whole luminaire shall be replaced.
- If the external flexible cable or cord of this luminaire is damaged, it shall be exclusively replaced by the manufacturer, his service agent or similar qualified person in order to avoid hazard.
- During installation or maintaining the luminaire please use gloves to avoid spots on the cover.
- To remove dust and spots use the following:
 - Dust: use micro fiber cloths only
 - Fingerprints, etc.: use a cleaner for synthetic materials with antistatic properties.
- The product is IPX0 & as such is not protected against water ingress & as such we strongly recommend that the environment in which the luminaire is to be installed is suitably checked.
- If the above advice is not taken and the luminaires are subject to water ingress, Signify cannot guarantee safe failure & product warranty will become void.