

INSTALLATION INSTRUCTIONS

L-980 LIVE END CONDUIT

TRACKER WITH 1/2" TRADE SIZE HOLE

For use with L650 Series Track system only
Electrical Rating: 120V, 60HZ, 20A

CATALOG NO.	FINISH
L-980	<input type="checkbox"/> P
	<input type="checkbox"/> MB

COOPER
Lighting Solutions

HALO LIGHTING
400 BUSSE ROAD
ELK GROVE VILLAGE, IL 60007

1/2" CONNECTOR IS NOT SUPPLIED

Step 1. Insert end of connector into track system. If connector does not slide into track, DO NOT FORCE. Track connector is polarized. Turn connector and use opposite ends. Ground contact on the same side as polarity groove track. After installation tighten screw of connector to secure to track.

Step 2. Remove covers (A) and (B) and attach 1/2" connector (not supplied) end. Then fasten conduit to connector.

Step 3. Pull wires into live end conduit thru oblong slot and connect to brass terminal, "P" white to nickel terminal "N" and (if green ground is available) connect to green ground screw. "G"

Step 4. Replace covers (A) and (B) and tighten screws.

Not necessary to wrap wire around screw.

696459

696459